1. Technical Energy Specifications Sheet, Cluster 3B

This information is compiled for Witchcliffe Ecovillage Cluster 3B lot owners and their builders and electricians.

2. Strata Cluster 3B Microgrid Features

This strata cluster features:

- 19 households
- Energy efficient, passive solar homes with heat pump hot water systems
- Min. 6kW PV panels per household
- Min. 5kW inverters per household
- 300A - 215kW micro-grid connection to Western Power grid
- Microgrid connecting each home to battery, 75kW EV charger and Western Power grid
- 232kWh Tesla Powerpack battery
- Single point connection to WP grid for sale of energy
- 75kW EV charger in Common Property parking area

A detailed analysis of the Cluster 3B energy budget is provided in Table 1 below.

Cluster 3B	Number of Lots	Min PV (kW)	Allocated Max Inverter size (kW)	Total inverter (kW)	Battery kW hour per lot	Total battery (kWh)
Groupies	5	6.6	3 Phase 5kW (Required)	25	7	35
Cottage	5	13.3	3 Phase 10kW	50	11	55
Family	9	20	3 Phase 15kW	135	15	135
Community Shed	1	6.6	3 Phase 5kW	5	7	7
Total	**20**			**215**		**232**

Table 1. Cluster 3B Energy Budget

Cluster 3B is estimated to collectively:

- **Produce** ~ 1075kWh / day of renewable energy (based on the maximum allowable installed PV & Inverters)
- **Use** ~215kWh / day (excluding EV charging)

3. Cluster 3B Household Energy Connection Requirements

Phases

All homes at the Ecovillage need to be wired for 3-phase power.

3-phase power allows for a more balanced distribution of loads across the three phases, which means that each phase carries a relative equal amount of power. A balance of power across phases reduces the risk of overloading and helps improve micro-grid power stability. 3-phase power can enable higher power loads than that of single-phase power making 3-phase power more suitable for use in houses with large solar arrays, residential batteries and EV chargers. It is essential that electricians balance loads as much as possible across the 3 phases in each home to enable the support of larger loads in the cluster such as EV chargers.

Meter

Each household must install an NMI certified meter. The National Metering Identifier (NMI) is a unique 10 or 11-digit number used to identify electrical network connection points in Australia. It is a requirement that every connection, including homes, are given their own NMI. It is not legal in Australia to trade energy across meters that are not NMI certified. NMI meters need to be SwitchDin Droplet (see below) compatible. 2 recommended Droplet compatible NMI meters are the SATEC and CET meter.

Droplet

To ensure Western Power approved energy management optimisation within our microgrids, residents are required to have SwitchDin "Droplets" installed at their property. We are pleased to inform you that the Witchcliffe Ecovillage developers have agreed to cover the cost of the "Droplet" hardware for all homes in Cluster 3B, as the new Western Power solar export control requirements came into being after their contracts were signed. Homeowners will pay for the installation of the Droplet. Integrated Electrical Contracting (IEC) has provided competitive 2023 pricing for the install of these Droplets at $191.90 + GST (on solar systems they installed). If you'd like to engage IEC to undertake this work (or quote on an install on a home that they didn't install the solar on) please contact their office at 0488 007 978. Alternatively, please contact your electrician for a quote for installation (they will need to have SwitchDin certification).

The Droplets will also read the household NMI meter and inverter and send this data to the Clusters SwitchDin Stormcloud which enables residents to view their energy use (import and export) and their Strata manager to see the overall cluster energy use and download CSV file to produce energy bills for each household.

By installing the SwitchDin Droplet it saves approximately $500 on a Fronius Smartmeter that would otherwise be required by Western Power. Solar systems cannot be turned on prior to droplets being installed.

Warranty issues need to be referred directly to Element 47, not the Developer. Meters can be replaced with either SATEC or CET meters if required in the future.

Inverter

In **Cluster 3B,** the microgrid compatible inverter brand and capacity required is the Fronius Symo with a minimum 3-phase 5kW inverter required for all homes:

- 3 phase 5.0kW (Required) for Groupie lots;
- 3 phase 10kW (Max) for Cottage lots, and
- 3 phase 15kW (Max) inverters for Family lots.

Internet

All Ecovillage households are required to provide an NBN connection for metering purposes.

Households that specifically do not want to connect to NBN must still provide a suitable microgrid control by either:

- providing an alternative internet connection for the Droplet via a suitable 4G wireless modem (not dongle); or
- purchasing the "Droplet +" and providing an activated Sim card and data plan, this however would be the most expensive option as the "Droplet +" supply cost is approximately $500 +GST.

The Droplet hardware requires at least a 4G modem with 2 free ethernet connections. WIFI connectivity via a dongle will not provide reliable enough coverage for accurate metering and monitoring, and for controlling the output of the solar system in peak times (as required by Western Power).

Solar systems

To provide an Ecovillage wide net neutral renewable power supply, all Ecovillage homes require the installation of a minimum of 6 kW solar PV. To maintain peak performance and efficiency of the overall cluster energy system, individual solar PV systems need to be installed and connected evenly across the cluster microgrid and careful consideration has been given to the servicing of each home and its permissible solar PV. The distribution of the systems over the network is critical to create a balanced network.

The size of solar PV system that is connected to each home will depend on the lot type that has been purchased. A breakdown of potential PV size and maximum inverter size is provided per lot type in Table 1, Cluster 3B Energy Budget.

4. Microgrid Connection Information

Connection Process

1. When your builder is ready to start works, they will inform our nominated electrical contractor, Integrated Electrical Contracting (IEC), that they require power within 2 weeks. Your builder will also inform IEC of the cable length required from the boundary of your lot to your home's meter box.
2. IEC will issue an invoice for the cable from your lot boundary to your home and for the NMI meter. Once paid IEC will then run a three-phase cable from the micro-grid's distribution board to your boundary, with sufficient cable to complete the run to your home when ready. The running of the cable from the boundary to the home is at the home owners' expense.
3. Your Builder/Electrical Contractor (EC) will then run a trench with the electrical cable to the location of your temporary power board.
4. Your Builder/EC then notifies IEC that the site is ready for an NMI meter and for IEC to make the connection to the grid.
5. IEC then notifies the affected cluster strata of up to a 1-hour outage (48 hours' notice).
6. IEC return to site, install the NMI meter, make the connection to the microgrid, test and commission. When your home is completed, the NMI meter and meter box will be transferred to your house.
7. Upon completion of internet connection your builder/electrician will organise to have your SwitchDin Droplet installed.

Additional Information / Requirements:

The below information needs to be provided to your builder and home designer.

- Each dwelling requires an externally accessible Western Power approved 450x450mm meter box. The LHS requires a minimum 16pole din kit with 1x 32amp 3 phase breaker.
- 32 Amp 3-Phase connection as per Western Power standard. Changes to the size of this connection are possible but will come at an additional cost.
- 25mm communications conduits need to be extended from the NBN pit on your lot boundary to enter directly into the LHS of the meter box with no more than 270 degrees of long radius sweep bends. This is to enable future microgrid controls.
- During electrical fitout electricians are required to ensure they run a 240v rated cat5e data cable from the internet modem location to the meter box and leave it 'made safe' and coiled behind the LHS panel with a data outlet terminated at the modem. This is to enable internet connectivity for the operation of Energy Management Systems i.e. Microgrid Controls & SwitchDin Droplets.
- Power connection points are at the rear of the lot. NBN connections are at the street side of the lots.

Indicative Connection Costs:

The 2023 indicative costs associated with this connection process are outlined below:

Requirement	Responsibility	Cost
3 phase cable from the micro-grid distribution board to your lot boundary	Developer – Providing homes commenced within contractual commencement date	Provided
NMI meter (Indicative Cost)	Home Owner	$506.40 + GST (Approx)
NMI meter installation at temporary power board and transfer to your home	Builder's Electrician	$180 + GST (Approx)
SwitchDin Droplet	Home Owner	$200 + GST (Approx)
SwitchDin Droplet installation – Energy Management	Home Owner	$191.90 + GST (Approx)

5. Solar system connection

The application process for solar system connections up to 30kW is as per standard residential applications and is relatively straightforward.

The process for connecting solar to the microgrid in clusters with greater than 30kW of installed solar capacity is as follows:

1. Solar systems are installed on residents' roofs.
2. Qualified Electrician will perform Power Quality Testing (PQT) to confirm stability of the cluster microgrid. During testing cluster microgrid power outages will apply, outage times will be communicated to residents in advance. This is a standard Western Power requirement for large solar systems.
3. Our engineers "Cossill & Webley" will perform "Grid Protection Testing" (GPT) to confirm our switchboard will operate correctly in the event the microgrid needs isolation from the Western Power grid. Depending on availability this step may be done before or after step 2. During testing cluster microgrid power outages will apply, outage times will be communicated to residents in advance.
4. "Grid Protection Testing" and "Power Quality Testing" data will then be consolidated and sent to Western Power for approval, this is our "Approval to Operate".
5. Once our "Approval to Operate" is received we are then able to activate solar systems that were included in that application.


TOURIST ROAD
EVC
1x100P (FUTURE BESS)
1x100P (SPARE)
1x63P (EV CHARGER)
1x20P
BL4-5
BL4-4
BL4-3
BL4-2
BL4-1
1x50P
2x50P
3x50P
1x100P (FUTURE BESS)
1x100P (SPARE)
1x63P (EV CHARGER)
2x40P (UNITS 18-19)
3x50P (UNITS 15-17)
1x20P (BOLLARDS)
2x20P
CONDUITS TO BE CONCRETE ENCASED UNDER OPEN DRAINAGE.REFER DETAIL ON DWG 3E19104-32
15
312m²
SOLAR PV
PHASE : BLUE
16
336m²
SOLAR PV
PHASE : WHITE
17
360m²
SOLAR PV
PHASE : RED
18
384m²
SOLAR PV
PHASE : BLUE
19
402m²
SOLAR PV
PHASE : WHITE
DB
BL3-1
14
1,023m²
SOLAR PV
PHASE : RED
1x100P (FUTURE BESS)
1x100P (SPARE)
1x80P (DB)
1x63P (EV CHARGER)
2x40P (UNITS 12-13)
1x50P (UNIT 11)
BL3-2
13
1,023m²
SOLAR PV
PHASE : WHITE
2x100P
1x80P
1x63P
1x40P
1x50P
BL3-3
12
1,023m²
SOLAR PV
PHASE : BLUE
2x100P
1x80P
1x63P
1x50P
CLUSTER 3B GARDEN/COMMON
12,692m²
BL3-4
11
1,023m²
SOLAR PV
PHASE : RED
1x100P (FUTURE BESS)
1x100P (SPARE
1x80P (DB)
1x63P (EV CHARGER)
1x40P (COMMUNITY SHED)
1x40P
COMMUNITY SHED
(BY OTHERS)
SOLAR PV
PHASE : RED
BL1-4
10
1,023m²
SOLAR PV
PHASE : WHITE
BL1-3
9
1,023m²
SOLAR PV
PHASE : BLUE
2x100P
1x80P
1x63P
1x40P
1x50P
BL2-1
BL2-2
BL2-3
BL2-4
BL2-5
1x20P
BL1-2
8
1,023m²
SOLAR PV
PHASE : RED
2x100P
1x80P
1x63P
2x40P
1x50P
1x20P
1x40P
4x50P
4x50P
3x50P
2x50P
1x50P
BL1-1
7
1,051m²
SOLAR PV
PHASE : WHITE
1x100P (FUTURE BESS)
1x100P (SPARE)
1x80P (DB)
1x63P (EV CHARGER)
1x40P (COMMUNITY SHED)
3x40P (UNITS 7-9)
1x50P (UNIT 10)
1x100P (SUPPLY)
WP
6
680m²
SOLAR PV
PHASE : BLUE
5
680m²
SOLAR PV
PHASE : RED
2x40P (UNITS 5-6)
4x50P (UNITS 1-4)
2x20P (BOLLARDS)
4
680m²
SOLAR PV
PHASE : WHITE
3
680m²
SOLAR PV
PHASE : BLUE
2
680m²
SOLAR PV
PHASE : RED
1
1,154m²
SOLAR PV
PHASE : WHITE
SMSB
1x32P
LP1-1
BATTLE AXE
KARRACK CRESCENT
MARDO DRIVE
NEW WESTERN POWER UNI PILLAR
TO BE INSTALLED UNDER SEPARATE CIVIL WORKS PROJECT. REFER TO DRAWING 3E#####-01 AND WESTERN POWER PROJECT SS######. REFER TO NOTES 16-18.